



Goal Zero - Power Stations

Yeti 200X

YETI 200X

The most lightweight power station to date, Yeti 200X delivers 187 Watt-Hours of lithium power and the latest fast-charging technology in a compact, ultra-portable design. Whether you're headed out for a few days or the whole week, you've got the perfect amount of power to keep your essentials charged from door to destination and back again.

Compact, Lightweight Power Station

The Yeti 200X Power Station delivers high-quality lithium power you can rely on, housed in an ultra-portable design made to take anywhere.

High-Speed Charging Solution

The Yeti 200X has a high-speed Power Delivery port capable of charging USB-C laptops, tablets, mirrorless cameras, and phones in a short time.

Solar Ready

Charge the Yeti 200X from the sun with portable solar panels while away from the grid and keep it topped off from a wall outlet when you're home.



Contact Danimex for more information or visit www.danimex.com/goal-zero

DMX-2020-03

Technical Specifications



YETI 200X			
CHARGE TIMES	<ul style="list-style-type: none"> • Maximum input: 2 Hours • Wall Charger: 4 Hours • Nomad 20: 12-24 Hours • Nomad 50: 5-10 Hours • Boulder 50: 5-10 Hours • Nomad 100: 2.5-5 Hours 		
PORTS	<ul style="list-style-type: none"> • USB-A port (output): 5V, up to 2.4A (12W max), regulated • USB-C port (output): 5-12V, up to 3A (18W max), regulated • USB PD port (input/output): 5-20V, up to 3A (60W max), regulated • 6mm port (output): 12V, up to 10A (120W max) • 12V car port (output): 12V, up to 10A (120W max) regulated • AC Inverter (output, modified sine wave): 230VAC, 50Hz, 0,5A (120W, 200W surge) • Charging port (input, 8mm): 13-22V, up to 7A (100W max), regulated 		
BATTERY DETAILS	<ul style="list-style-type: none"> • Cell Chemistry: Li-ion NMC • Peak Capacity: 187Wh (14.4V, up to 13Ah) • Lifecycles: 500 cycles to 80% (discharge rate: 1C, full charge/discharge, Temp 25C) • Shelf-life: Keep plugged in, or charge every 3-6 months • Management system: MPPT charge controller, low battery protection 		
GENERAL	<ul style="list-style-type: none"> • Product SKU: 22080 • Chainable: No • Weight: 5 lbs (2.27 kg) • Dimensions 7.9 x 5.1 x 5.1 in (20 x 13 x 13 cm) • Operating Usage Temp: 32-104F (0-40C) • Warranty: 24 Months 		
RUN TIME	<table border="0" style="width: 100%;"> <tr> <td style="vertical-align: top;"> Recharges <ul style="list-style-type: none"> • Smart Phone (12 Wh): 16 • Tablet (30 Wh): 6 • Laptop (50 Wh): 4 • POV Camera (5 Wh): 38 • DSLR Camera (18 Wh): 11 • Head Lamp (5 Wh): 38 </td> <td style="vertical-align: top;"> Hours of Runtime <ul style="list-style-type: none"> • GZ Light (4.5 Wh): 41.5 • Light Bulb (11 Wh): 17 • Portable Fridge (25 Wh): 8 • Full Size Refrigerator (55 Wh): 20 </td> </tr> </table>	Recharges <ul style="list-style-type: none"> • Smart Phone (12 Wh): 16 • Tablet (30 Wh): 6 • Laptop (50 Wh): 4 • POV Camera (5 Wh): 38 • DSLR Camera (18 Wh): 11 • Head Lamp (5 Wh): 38 	Hours of Runtime <ul style="list-style-type: none"> • GZ Light (4.5 Wh): 41.5 • Light Bulb (11 Wh): 17 • Portable Fridge (25 Wh): 8 • Full Size Refrigerator (55 Wh): 20
Recharges <ul style="list-style-type: none"> • Smart Phone (12 Wh): 16 • Tablet (30 Wh): 6 • Laptop (50 Wh): 4 • POV Camera (5 Wh): 38 • DSLR Camera (18 Wh): 11 • Head Lamp (5 Wh): 38 	Hours of Runtime <ul style="list-style-type: none"> • GZ Light (4.5 Wh): 41.5 • Light Bulb (11 Wh): 17 • Portable Fridge (25 Wh): 8 • Full Size Refrigerator (55 Wh): 20 		
RECOMMENDED SOLAR PAIRINGS	<p>Standard Usage Nomad 20: Charges in 12-24 Hours</p> <p>Heavy Usage Nomad 50: Charges in 5-10 Hours</p> <p>*Solar charge times vary and are dependent on many factors such as elevation, temperature, time of year, angle and position to the sun.</p>		
THREE WAYS TO CHARGE THE YETI POWER STATION	<p>From the Sun - Recharge from the sun by connecting a compatible solar panel.</p> <p>From the Wall - Plug it into the wall. Fully recharges in 4 hours using included power supply.</p> <p>From the Car - Plug into your vehicle's 12V outlet using the Goal Zero Yeti Lithium 12V Car Charging Cable</p> <p>NOTE: Do not attempt to charge your Yeti Lithium from a 12V source using any other cable. Doing so may cause damage to the unit.</p>		